



Expand
Your
RMR



See reverse side for full list of features.

FEATURES:



FULLY SUPERVISED

Pendants communicate with base station every 13 hours to ensure proper connection. Central station is contacted in the event of a power outage, low battery or loss of RF signal. Central Station is contacted every 52 hours if 4 tests are missed.




AUDIBLE PROMPTS

Audible prompts can be heard during system set-up, system programming, testing and full system check.



SOS CALL

Emergency call is placed by pressing the 'EMERGENCY' button on the pendant.



TWO-WAY AUDIO

Small, portable pendant provides exceptional communication upon system activation.



BUILT-IN LINE-SEIZURE

This feature allows for the telephone line to be seized during an emergency call.



STATUS INDICATORS

System information (announced during system check), pendant battery charge and AC power are displayed by 3 LEDs.



MONITORED SERVICE

All calls are routed to a 24/7 monitored station. The programmed number is called only upon activation from the button on the pendant.



PROGRAMMING

Program to any central station. Program the primary and secondary receiver numbers. Enter your 4 digit account number. Enter your 4 digit dealer code. Choose between monthly, weekly or daily test timers. Can be programmed remotely over the phone.



BATTERY BACK-UP

Base unit includes rechargeable batteries for up to 24 hours of emergency battery power in the event of a power outage.

SPECIFICATIONS:

- Central Station: Contact ID and 4+2 formats
- Compatibility: POTS & most VoIP systems
- Coverage: up to 600ft (183m) line of sight
- Up to 4 pendants can be associated with a single base

- Battery: Four AA NiMH rechargeable for base backup power
One 3.7V Li-ion rechargeable for 2-way voice pendant (plus one spare included)
- Two-way voice communication technology using 1.9GHz Digital Enhanced Cordless Telecommunications (DECT)